

Claim Amendments

1. (currently amended) A method of interfacing for packet and cell transfer between a first layer device and a second layer device, in which control information is divided into an in-band portion and an out-of-band portion, comprising:

~~(a) dividing control information into an in-band portion and an out-of-band portion;~~

(a) transmitting the in-band portion ~~together with data in a data path of said control information~~ along a physical path which is the physical path for data from one of said first and second layer devices to another of said first and second layer devices; and

(b) inserting in said data path a control of data signal to identify when the data path contains control information and when it contains data;

~~(c) transmitting the out-of-band portion outside of the data path from said another of said first and said second layer devices to said one of said first and said second layer devices~~

whereby re-encoding of data and insertion of control information upon pre-determined intervals is avoided.

2. (currently amended) A method according to claim 1, wherein said in-band portion is ~~transfer specific information~~ control

information as to status and destination address of data being sent and to align parallel data lines that comprise a data path and said out-of-band ~~information~~ portion is credit-based FIFO status flow control information -
whereby said ~~interface operates independently in both transmit and receive directions~~ interfacing is done independently in both transmit and receive directions and a number of credits granted to each port depends on an encoded state of a corresponding port status.

3.(original) A method according to claim 2, including using a "1 1" framing pattern on a FIFO status channel to mark boundaries of the framing pattern without requiring an out-of-band framing signal.

4.(original) A method according to claim 1, including sending a training control pattern sufficiently often in order to allow a receive interface to check and correct for de-skew on start-up and during regular operation to compensate for skew variations due to changes in voltage, temperature, noise and other factors.

5.(original) A method according to claim 1, using a clock in a direction opposite to the data path as a reference source for

the data path transmitting from a side of the interface opposite to a transmitting end.

6.(original) A method according to claim 4, wherein a transmitting end of the data path sends data and control signals precisely aligned with respect to a source-synchronous clock and the training pattern once every MAX_T where MAX_T is configurable on start-up.

7.(original) A method according to claim 1, wherein each control word contains an error-detection code and one or more control words are inserted between bounded transfer periods whereby performance of the code is not degraded by overly long transfers.

8.(original) A method according to claim 1, wherein an end-of-packet event and error codes are combined into a two-bit code to reduce the number of bits required.

9.(original) A method according to claim 1, wherein transfer information referring to a previous transfer and to a next transfer is contained in one control word.

10. (currently amended) A method according to claim 1, wherein ~~transfer information referring to a previous transfer and to a next transfer is contained in one~~ a single control word may contain control information that applies to data preceding said single control word as well as data following said single control word.

11. (currently amended) A method of interfacing for packet and cell transfer between a first link layer device and a physical second layer device, in which control information is divided into an in-band portion and an out-of-band portion, comprising:

~~(a) dividing control information into an in-band portion and an out-of-band portion;~~

(a) transmitting the in-band portion together with data in a data path of said control information along a physical path which is the physical path for data from one of said link layer device and said PHY first and second layer devices to another of said link layer device and said PHY first and second layer devices;

(b) inserting in said data path between data transfers a control of data signal to identify when the data

path contains control information and when it
contains data; and

(c) transmitting FIFO status flow information out-of-
band;

~~(e) transmitting the out-of-band portion outside of the~~
~~data path from said another of said link layer~~
~~device and said PHY to said one of said link layer~~
~~device and said PHY~~

whereby re-encoding of data and insertion of control
information upon pre-determined intervals is avoided.

12. (currently amended) A method according to claim 11, wherein
said first layer device is a PHY and said second link layer
device has a transmit link layer device operative to transmit
data from said transmit link layer device to said PHY and a
receive link layer device operative to ~~transmit data from said~~
~~first layer device to~~ receive data from said PHY ~~to said receive~~
~~link layer device.~~

13. (original) A method according to claim 11, wherein said in-
band portion includes packet address, delineation and error
control coding and said out-of-band information is FIFO status
flow information whereby said interface operates independently
in both transmit and receive directions.

14.(original) A deskewing circuit for deskewing data arriving on a plurality of data lines, comprising:

(a) a plurality of serial-in parallel out (SIPO) blocks coupled to said plurality of data lines operative to convert serial input data from a corresponding respective plurality of data lines to parallel data;

(b) a plurality of registers coupled to said SIPO blocks, said registers operative to store successive words of data arriving on said data lines with one word stored on each of said registers;

(c) a training detector block coupled to said registers and operative to detect the presence of a training pattern based on the contents of said registers;

(d) a plurality of transition detection blocks coupled to said registers and operative to search and to detect a transition in each bit position of said registers;

(e) an aligner block coupled to said transition detection blocks operative to select an appropriate register

from which to read each bit in order to present a deskewed output.

15.(original) A deskewing circuit, comprising:

(a) 17 serial-in parallel-out (SIPO) blocks, each one coupled to a corresponding input data line and operative to convert serial input data to parallel output data, each of said SIPO blocks having N outputs where N is an integer equal to a word size of data output from each of said SIPO blocks, each of said SIPO blocks having separate bit outputs for each bit of a word converted by said each of said SIPO blocks;

(b) N registers coupled to said separate bit outputs of each of said SIPO blocks such that an i^{th} one of said N registers is connected to an i^{th} bit output of said SIPO blocks, where $i=1, 2, \dots, N$;

(c) a training detector block coupled to outputs of said registers operative to detect the presence of a training pattern based on the contents of said registers;

(d) 17 transition detection blocks coupled to outputs of said registers with an i^{th} transition detection block coupled

to an i^{th} bit output of each of said registers, where $i=1, 2, \dots, 17$, said i^{th} transition detection block, when after the presence of a training pattern has been detected, is operative to search for a transition on an i^{th} bit position from said 17 registers; and

(e) an aligner block coupled to outputs from said 17 transition blocks operative to select an appropriate register from which to read each bit in order to present a deskewed output.